

# AB360

6" Fire Bell For Indoor Use, 24Vdc

## General

---

The AB360 is a 150 mm (6 inch) internal bell designed as an acoustic fire annunciator. Thanks to its small dimensions and overall design, it is ideal for in-door installation. The AB360 uses a 24 VDC supply and with the advantage of having very low current consumption, makes them compatible with most fire alarm systems on the market.

## Applications

---

The AB360 is ideal for installing on any site, but are specifically good for installing on sites where a great number of bells are required. Because of the low current consumption, excessive power supplies can be avoided.

## Construction

---

Designed for ease of installation, the AB360 features a robust steel gong. This ensures the reliable generation, of the universally recognizable fire alarm bell sound.



## Standard Features

---

- Suitable for indoor use
- Slim profile
- Low current consumption - 20mA
- Quick and easy installation
- Diode polarised
- Low maintenance
- Very reliable
- EN54-3 Approved
- CPD compliant

# AB360

6" Fire Bell For Indoor Use, 24Vdc

## Specifications

Electrical	
Operating voltage	19 to 28 VDC
Current consumption	20 mA
Physical	
Net weight	920 g
Colour	Red
Environmental	
Environment	Indoor
IP rating	IP21C
Temperature Range	-10 to +55 °C
Standards & regulation	
Certification	EN54-3
Physical Characteristics	
Sound Output	95 dB(A)
Diameter	6" (150 mm)
Gong construction	Steel

## Ordering Information

Part No.	Description
AB360	6" Fire Bell For Indoor Use, 24Vdc